

# Quick action

## Actions



Each XMPP relay has a set of **rapid action** which allow direct interaction with the machines it manages. These actions are accessible from the **list of relays** and are designed to simplify the day-to-day operations of administration, diagnosis or configuration, without requiring advanced technical knowledge.

Here is a detailed overview of each action, its usefulness and the procedure for using it.

## 1. See the list of installed packages

### Objective

View software installed on machines attached to a relay.

### Procedure

[pkgs.png](#)

1. Click on the button "**List of packages**" to the right of the relay concerned.
2. A window opens displaying installed software, with its name and version.

### When to use

- To verify the presence of a program.
- To control deployed software versions.

## 2. Reconfigure relay related machines

### Objective

Automatically reapply the active configuration to the machines attached to the relay.

### Procedure



1. Click "**Reconfigure**".
2. Confirm the action if validation is requested.
3. The machines are again given the current configuration.

#### **When to use**

- After changing the settings, rules or configuration files.
- If a machine appears to be unsynchronised or non-compliant.

### **3. Change the relay of one or more machines (Switch function)**

#### **Objective**

Move one or more machines from one relay to another.

#### **Procedure**



1. Click **Switch** to the right of the original relay.
2. Select the moving machines.
3. Choose the destination relay.
4. Validate to apply the change.

#### **When to use**

- In case of maintenance or removal of a relay.
- During a reorganization of the network architecture.

### **4. Edit Configuration Files**

#### **Objective**

Manually modify the configuration files of a relay or its machines.

#### **Procedure**



1. Click "**Edit configuration files**" (**first working image**)
2. An editing interface opens.
3. Make the necessary changes.
4. Save the changes.

#### **When to use**

- To adjust a specific configuration to a specific need.
- During a test or manual procedure.

**Note** This operation acts directly on the system. Use with caution.

## **5. Show current or past audits (QA)**

#### **Objective**

Consult compliance, safety or quality tests performed on machines.

#### **Procedure**



1. Click "**QA launched**".
2. A window displays the list of tests performed and their status (successful or failed).

#### **When to use**

- To check that the rules are being applied.
- To identify possible malfunctions.

## **6. Access system actions (advanced diagnostic)**

#### **Objective**

Use remote diagnostic or intervention tools on a machine.

## Procedure



1. Click **Action** Next to the relay.
2. Select one of the available options:
  - **Reboot** : restarting the machine.
  - **Process** : visualization of processes in progress.
  - **Disk use** : consultation of the disk space used.
  - **Agent version** : version of software agent installed.
  - **Netstat** : display of active network connections.
  - **Console** : opening of a command line interface.

## When to use

- When a machine is broken, slowed or unstable.
- For quick diagnosis or manual verification.

## 7. Banning a machine

### Objective

Temporarily block a machine's access to the system.

## Procedure



1. Click "**Bannir**" Next to the relay.
2. Confirm the banner.
3. The machine is isolated from the rest of the network.

## When to use

- In case of abnormal behaviour, suspicion of compromise or critical error.

## 8. Debanniating a machine

## Objective

Lift the block applied to a previously banned machine.

## Procedure



1. Click "**Debannier**".
2. The machine regains its normal communication rights.

## When to use

- After correcting the initial problem.
- If the machine was incorrectly blocked.

## 9. Remote control

### Objective

Control a machine remotely as if you were physically in front of it.

### Procedure



1. Click "**Hand-to-hand**".
2. A remote session opens, allowing you to interact with the machine's graphical interface.

## When to use

- To intervene manually.
- To diagnose a specific problem.
- When no other automated action is enough.

## 10. Manage relay rules

## Objective

Consult, modify or add specific operating rules to a relay.

## Procedure



1. Click "**Relay rules**" (**last working image**)
2. From the interface:
  - View existing rules.
  - Change or delete outdated rules.
  - Add new rules as needed.

## When to use

- To automate repetitive actions.
- To dynamically adapt the relay behavior to a specific use.

---

Revision #1

Created 12 May 2025 14:16:00 by DocsAdmin

Updated 12 May 2025 14:16:09 by DocsAdmin